

- SIMPLE TO INSTALL
- ELIMINATES ILLEGALLY WEDGED DOORS
- CE MARKED
- AESTHETICALLY PLEASING

WHY GO TO THE EXPENSE OF INSTALLING A FULL FIRE SYSTEM WHEN YOUR ONLY NEED IS TO HOLD CORRIDOR DOORS OPEN ?



The Fire Door Sentry Kit is a complete stand alone CE approved fire door control system that dependant on choice may or may not be wired into an existing fire system. Never again will there be a need to see internal doors wedged open or held open with fire extinguishers.

The pack consists of a control panel, two detectors and a fire door holder. This permits control of one fire door. The basic pack can be expanded to control up to 8 fire door holders and allows staggered closing of double doors to ensure they close correctly.

The kits supply voltage is 230Vac which it internally regulates via the control box to 24Vdc to power the smoke detectors and door holder.

Additional door holders and smoke detectors are available. The kit also supports the use of fire alarm sirens and bells.



TECHNICAL INFORMATION

Supply Voltage	230VAC/24VDC
Operating Voltage	24VDC
Current Consumption in normal operation	50mA (not including magnets)
EOL Smoke Detector section	2.2kOhm
EOL Bell/Siren section	2.2kOhm
Fuse	PTC resistor on 230V inlet with automatic reset
Weight	Ca 0.5kg
Max. load	400mA
Dimensions	110 x 150 x 40mm
Part Number	3-90-1000

EOL = End of Line Resistor

Unit tested by Delta in Denmark and approved by the Danish Fire Technology Institute.

A COMPLETE FIRE DOOR SENTRY KIT CONTAINS:

2 PHOTOELECTRIC SMOKE DETECTORS

1 ELECTROMAGNETIC DOOR HOLDER (200N HOLDING FORCE)

1 KEEPER PLATE

1 CONTROL BOX WITH VISUAL ALARM/FAULT INDICATORS

INCLUDES TEST AND RESET OPTIONS

230Vac SUPPLY VOLTAGE

Geofire reserve the right to change the specifications in this data sheet without prior notification