

### PRODUCT CODE

3-89-0301 - Fire Door Holder

### APPLICATION

This electromagnetic door holder is for retaining swinging fire doors open for ease of access in busy buildings. It is designed for use with a separate door closer and separate fire detection system. The magnet and fascia plate are suitable for flush mounting with a standard back box or for surface mounting with the supplied enclosure.



### TECHNICAL SPECIFICATION

- HOLDING FORCE ..... 25lb force (112N)
- RESIDUAL FORCE ..... Zero
- ELECTRICAL SUPPLY..... Multi-input:- 24 V ac, 24 V dc or 120 V ac
- CURRENT..... 20 mA
- AMBIENT TEMPERATURE ..... 0 - 25° C
- KEEPER ADJUSTMENT ..... + / - 45°
- UL LISTING ..... PENDING

### CONSTRUCTION

- MAGNET AND KEEPER PLATE ..... Machined steel, nickel plated.
- FACIA PLATE ..... Pressed steel. Available in painted silver finish or chrome plated.
- KEEPER MOUNTING BASE ..... Die cast zinc alloy. Finishes as per the facia plate.

### ACCESSORIES

- KEEPER EXTENSION PIECES ..... 6” and 12”
- SURFACE MOUNT BOX ..... Sheet steel, painted

3-89-0901 Issue 1/08